

# KYOCERA® FS-1370

## EASY TO REMANUFACTURE CARTRIDGE INSTRUCTIONS



KYOCERA FS-1370 TONER CARTRIDGE

# REMANUFACTURING THE KYOCERA FS-1370 TONER CARTRIDGE

By Mike Josiah and the Technical Staff at UniNet



The Kyocera FS-1370 cartridges are rated for 7,500 pages.

The OEM part numbers are 170, 172, 173, 174 (depending on your region).

There is a chip used on this cartridge that must be replaced each cycle.

The chips are regional so make sure you have the correct one!



1. Drill a 1/2" to 3/4" hole into the fill plug. The OEM plugs are welded in so the hole is necessary. Clean out all the remaining toner.



2. Make sure the toner port is closed.



3. Fill the cartridge with toner for use in the TK-170 series of cartridges. Use a Samsung CLP-300 seal to cover the hole you drilled.



4. If shipping the cartridge, place a small strip of tape across the toner port.



5. Peel off the old chip label (it is an RF type chip).

Install the new chip label.

UniNet®